

ALABAMA NET OPERATIONS GUIDE
ANNEX A

NET CONTROL STATION SCRIPT

Open the Net:

4A1B, 4A1B THIS IS (NCS), TRAFFIC REPS ONLY, OVER

*** *Take list*

(Call off list) THIS IS (NCS), ROGER, OUT

Call for Stations with Traffic:

4A1B THIS IS (NCS), STATIONS WITH RECORD TRAFFIC ONLY. OVER.

*** *Take list*

(Call off list) THIS IS (NCS), ROGER, OUT.

(If no stations heard) THIS IS (NCS), NO STATIONS HEARD, OUT

Call for Additional Stations:

4A1B THIS IS (NCS), OVER

*** *Take list*

(Call off list) THIS IS (NCS), ROGER, OUT.

(If no stations heard) THIS IS (NCS), NO STATIONS HEARD, OUT

Repeat call for Additional Stations:

Call for relays and net call:

(selected station) THIS IS (NCS), REPORT RELAYS AND MAKE A
NET CALL. OUT.

*** *Take list from Net Call station - -* THIS IS (NCS) ROGER, OUT.

(Call off list) THIS IS (NCS), ROGER, OUT.

Authorizing Abbreviated Call Signs:

4A1B THIS IS (NCS), ABBREVIATED CALL SIGNS AUTHORIZED. OUT.

Direct passing of messages per Part II, paragraph 5.d

Authorizing a Free Net:

4A1B THIS IS (NCS), ARE THERE ADDITIONAL STATIONS OR
BUSINESS FOR THE NET BEFORE THE FREE NET, OVER

(If response, take action as appropriate)

(If no stations heard) THIS IS (NCS), NO STATIONS HEARD, OUT

4A1B THIS IS (NCS), THIS IS NOW A FREE NET. STATIONS MAY CLOSE
DOWN AT WILL.

(If necessary) GIVE PRIORITY TO (call) AND (call). OUT.

Last Call:

4A1B THIS IS (NCS), ARE THERE ADDITIONAL STATIONS OR
BUSINESS FOR THE NET BEFORE THE NET IS CLOSED, OVER.

(If response, take action as appropriate)

(If no response) THIS IS (NCS), NO STATION HEARD, OUT.

Securing the Net:

4A1B THIS IS (NCS), CLOSE DOWN. OUT.